

CLAIMS

1. Device for servo-control of a dental handpiece (5) activated by an ultrasound generator, comprising supply means (1), characterized in that:

- it comprises two circuits, namely a work circuit to whose terminals (S1, S2) the ultrasound generator is connected, and a control circuit,

- the work circuit comprises an inductance (L_s) in parallel between its output terminals (S1, S2),

- the supply (1) is adapted to deliver at the output (A, B) a voltage (V_s) in phase with a voltage which is delivered thereto on its input (I, J),

- the control circuit is constituted by an intensity transformer (T_2) whose primary (7) is arranged in series in the work circuit and whose secondary (11) forms, with a capacitor (13) and a resistor (15) associated therewith, an RLC circuit of which the voltage at the terminals of the resistor (15) is sent to the input of said supply (1),

- the control circuit comprises means for varying the value of the capacitor (13) and/or that of the self-induction coil of the secondary (11) of the transformer (T_2).

2. Device according to Claim 1, characterized in that the secondary (11) of the intensity transformer (T_2) comprises a core mobile inside its winding adapted to vary its inductance (L_2).

20010101 23561001

3. Device according to one of Claims 1 or 2, characterized in that the supply means (1) are connected to the work circuit via a voltage transformer (T_1).
4. Device according to one of the preceding Claims, characterized in that the
- 5 inductance (L_s) arranged between the output terminals (S_1 , S_2) of the work circuit is such that, with the intrinsic capacitance of the handpiece (5) and the internal resistance thereof, an RLC circuit close to the resonance is formed.

202010 256T007 10019527 040202